


FritzBox7390 - Setting up voice mail


1. Fritzbox login

Open the internet browser (e.g. MS Internet Explorer) on your computer and enter the IP address <http://192.168.178.1/> or <http://fritz.box/>.



After activating your Fritzbox via the browser, please enter your password, which you set at your first login. If you have not set a password, you can enter your router password here.

Click on 'Log On'



2. Preparation


2.1 Change to Expert view

- Click on 'System' in the menu and then on 'Expert Mode'
- Activate Expert view by checking 'Advanced View'
- Click on 'Apply'



2.2 Save internet phone number on the Fritzbox

- Select 'Telephony' and then 'Own Telephone Numbers'
- Click on the 'notepad symbol' next to your phone number



- Confirm all information without making changes in the next window by clicking on 'OK'. If you have several phone numbers, this step must be repeated for each number.

2.3 Assign telephony device

- We recommend that you assign your devices that are connected to the Fritz!Box.
- To do this, select 'Telephony' and then 'Telephony devices' and click on 'Configure New Device'.

- Under 'Connected to the Fritz!Box' choose the device that you have connected with the Fritz!Box.
- Confirm your entry with 'Next'

- On the next page, select the connection that your device is connected to.



FRITZ!Box 7390

Connecting a Telephone

1. Connect the telephone to a suitable FON socket on the FRITZ!Box or keep your cordless (DECT) or IP phone ready.
2. Select the port at which you want to operate the telephone.
 - FON 1 (analog telephone)
 - FON 2 (analog telephone)
 - FON SO (ISDN telephone)
 - DECT (cordless telephone)
 - LAN/WLAN (IP telephone)
3. Enter a name for the telephone, for example "living room" or "Anna's phone":

Telephone

Back Next Cancel

- In the next step the Fritz!Box will check whether the connection to your device works properly. If the function test is successful (the end device rings) confirm the question with 'Yes'



FRITZ!Box 7390

Testing the Telephone Connection

If the telephone rings now, it is connected correctly and assigned to the right line.

Is the telephone ringing?

Yes No

- You should now select the phone number that your device should respond to. If your Sunrise TV product contains more than one phone number, all numbers can be selected by clicking on 'accept all calls', or selected individually by clicking on 'accept calls for the following numbers only' below this.
- Confirm your entry with 'Next'



FRITZ!Box 7390

Configuring Telephone Settings for Incoming Calls

Specify whether the telephone should accept all calls or only react to certain telephone numbers.


- accept all calls
- accept calls for the following numbers only:
 - 044 (number for outgoing calls)

Back Next Cancel

- You will now see an overview of the settings that you have changed. You can modify these again by clicking on 'Back' or save these changes by clicking on 'Apply'.




- A new line will now appear on your list of telephony devices entitled 'Telephone' (or the personalized name that you have set)




3. Setting up voice mail

- To set up the built-in voice mail, select 'Telephony' from the main menu and then click on 'Telephony devices'
- Click on 'Configure New Device'.



- To use the built-in voice mail, select 'Answering machine' under 'Intergrated in the Fritzbox'
- Click on 'Next'



- To record messages, select 'Record messages' from the drop-down list next to 'Operating mode'
- You can set the time it takes the built-in voice mail to pick up under 'Greeting delay'
- You can restrict the caller's speaking time under 'Recording length'
- If you would like to set different values for individual phone numbers, you can give the relevant voice mail a different name in point 2. This can make later modifications easier.
- After you have changed all settings to suit your requirements, confirm your changes by clicking on 'Next'



- You can now select the phone number that the built-in voice mail should respond to. If your Sunrise TV product contains more than one phone number, all numbers can be selected by clicking on 'accept all calls', or selected individually by clicking on 'accept calls for the following numbers only' below this.
- Confirm your entry with 'Next'.



- You will now see an overview of the settings that you have changed. You can modify these again by clicking on 'Back' or save these changes by clicking on 'Apply'.



FRITZ!Box 7390

Apply Settings

Configuring the answering machine with the following settings.

Telephony device	Integrated answering machine
Name	Answering machine 1
Operating Mode	Record messages
Greeting delay	20 seconds
Recording length	60 seconds
Use USB storage device to increase recording capacity	No
Numbers for incoming calls	all incoming calls

Tip:

- To listen to messages and to configure the answering machine, dial **600.
- Newly arrived messages are signaled by a flashing INFO LED on the FRITZ!Box.

To save the settings in the FRITZ!Box, please click "Apply".

Back Apply Cancel

- A new line will now appear on your list of telephony devices entitled 'Answering machine 1' (or the personalized name that you have set)



FRITZ!Box 7390

Set password Expert Mode: Advanced Contents Help

Overview

Internet

Telephony

Calls
Telephone Book
Alarm
Call Blocks
Call Diversion
Dialing Rules
Telephony Devices
Own Telephone Numbers
Regional Options

Home Network

WLAN

DECT

System

Telephony Devices

On this page you can configure and edit the telephones, answering machines and fax machines connected to the FRITZ!Box.

Name	Connected Via	Number	Outgoing	Incoming	Internal		
Answering machine 1	integrated	-		All	**600		
Telephone	FON 1	044		All	**1		

Print List Configure New Device Help

4. Personalize the voice mail

Once you set up the voice mail on the Fritz!Box, this can be customized via the voice menu.

To do this, take one of the phones that is connected to the Fritz!Box and call the internal number for the voice mail. The default number is ****600**.

If several voice mails were set up, find their internal numbers under '**Telephony devices**' in column entitled '**Internal**'.

The voice menu will guide you through the settings.

Important: The voice menu is only available in German and English

The exact structure of the voice menu can be found here:

<http://service.avm.de/support/de/SKB/FRITZ-Box-7390/10:Anrufbeantworter-ueber-Sprachmenue-bedienen>

4.1 Recording a personalized message

- Select the internal number for the desired voice mail (default number: ****600**).
- After the first prompt press 4.
- Now press 1 to create a new greeting message.
- You can now start a new recording by pressing 8 – speak after the tone. Stop the recording by pressing 1.
- If you wish, you can now listen to the newly recorded message again by pressing 0.